



ЭЛЕКТРОННАЯ ПРОДУКЦИЯ > ПРОДУКТЫ УПРАВЛЕНИЯ ЭНЕРГИЕЙ > СЧЁТЧИКИ ЭЛЕКТРОЭНЕРГИИ

B80-0M-O2P

Артикул (SKU): 606368

1Ø счетчик энергии MID

Коммерческая информация

Код продажи продукта	606368
Единица Упаковки	1 шт.
Номер таможенного тарифа	903032009011
Вес за единицу, включая упаковку	0.12 kg.

Техническая информация

General	
Connection Type	1P2W
Real Time Clock	
Current Connection Type	Direkt Baglantili (45A ya kadar)
Alarm	
Energy Measurement	
Number Of Tariffs	1
Number Of Sub Tariffs	
Number Of Reactive Measurement Zones	2
Energy Measurement Type	Import & Export kWh-kVArh
Partial Counter	+
Balance Energy	

Current Measurement Input

Measuring Range	0,25 .. 80A
-----------------	--------------------

Voltage Measurement Input

Measuring Range L N	100-300V AC
---------------------	--------------------

Measuring Range L L	-
---------------------	---

Power Quality Measurements

Harmonic Measurement Current And Voltage	-
--	---

Thdi	
------	--

Thdv	
------	--

Power Supply

Voltage	100-300V AC
---------	--------------------

Frequency	45-65Hz
-----------	----------------

Consumption	<3VA AC
-------------	-------------------

Mechanical Properties

Weight G	120
----------	------------

Protection Class	IP20
------------------	-------------

Mounting Type	Rail Mount
---------------	-------------------

Environmental Conditions

Operating Temperature	-25°C +50°C
-----------------------	--------------------

Storage Temperature	-25°C +70°C
---------------------	--------------------

Relative Humidity Non Condensing	Max. 80% (no condensation)
----------------------------------	-----------------------------------

Communication

Protocol	
----------	--

Baud Rate	
-----------	--

Parity	
--------	--

Stop Bit	
----------	--

Slave Id	
----------	--

Isolation	
-----------	--

Digital Output

Frequency	5-30 VDC
Number Of Inputs	2 (sabit)
Switched Voltage Range	Transistor
Isolation	3750 Vrms

Digital Input

Number Of Inputs	
Input Type	
Isolation	

Other Measurements

Operating Time Counter	
Open Time Counter	
Power Failure Counter	

Basic Electrical Measurements

Current	+
Voltage	+
Frequency	+
Active Power	+
Reactive Power	+
Apparent Power	+

Cable Cross Sections Power Supply Voltage Relay

multi-core	
Single Core	

Cable Cross Sections Current

multi-core	
Single Core	

Cable Cross Sections Digital Inputoutput Rs485 Analog Output

multi-core	
------------	--

Single Core

Measurement Class

En 50470

Class B

62053 21

Measurement

Max Min Data

Demand

+

Led Impulse

Kwh

+

Kvarh

+