



ЭЛЕКТРОННАЯ ПРОДУКЦИЯ > ПРОДУКТЫ УПРАВЛЕНИЯ ЭНЕРГИЕЙ > СЧЁТЧИКИ ЭЛЕКТРОЭНЕРГИИ

B100-0M-V3CT

Артикул (SKU): 606806

3Ø счетчик энергии MID

Коммерческая информация

Код продажи продукта	606806
Единица Упаковки	1 шт.
Номер таможенного тарифа	903032009011
Вес за единицу, включая упаковку	0.34 kg.

Техническая информация

General	
Connection Type	3P4W & 3P3W
Real Time Clock	
Current Connection Type	CT Baglantili
Alarm	
Energy Measurement	
Number Of Tariffs	2
Number Of Sub Tariffs	
Number Of Reactive Measurement Zones	2
Energy Measurement Type	Import & Export kWh-kVArh
Partial Counter	+
Balance Energy	+

Current Measurement Input

Measuring Range	0,05 .. 6A
-----------------	-------------------

Voltage Measurement Input

Measuring Range L N	100-300V AC
---------------------	--------------------

Measuring Range L L	173-520
---------------------	----------------

Power Quality Measurements

Harmonic Measurement Current And Voltage	
--	--

Thdi	+
------	----------

Thdv	+
------	----------

Power Supply

Voltage	100-300V AC
---------	--------------------

Frequency	45-65Hz
-----------	----------------

Consumption	<3VA AC
-------------	-------------------

Mechanical Properties

Weight G	340
----------	------------

Protection Class	IP20
------------------	-------------

Mounting Type	Rail Mount
---------------	-------------------

Environmental Conditions

Operating Temperature	-25°C +50°C
-----------------------	--------------------

Storage Temperature	-25°C +70°C
---------------------	--------------------

Relative Humidity Non Condensing	Max. 80% (no condensation)
----------------------------------	-----------------------------------

Communication

Protocol	
----------	--

Baud Rate	
-----------	--

Parity	
--------	--

Stop Bit	
----------	--

Slave Id	
----------	--

Isolation	
-----------	--

Digital Output

Frequency	5-30 VDC
Number Of Inputs	2 (1 sabit, 1 ayarlanabilir)
Switched Voltage Range	Transistor
Isolation	3750 Vrms

Digital Input

Number Of Inputs	2
Input Type	Dry Contact
Isolation	3750 Vrms

Other Measurements

Operating Time Counter	
Open Time Counter	
Power Failure Counter	

Basic Electrical Measurements

Current	+
Voltage	+
Frequency	+
Active Power	+
Reactive Power	+
Apparent Power	+

Cable Cross Sections Power Supply Voltage Relay

multi-core	
Single Core	

Cable Cross Sections Current

multi-core	
Single Core	

Cable Cross Sections Digital Inputoutput Rs485 Analog Output

multi-core	
------------	--

Single Core

Measurement Class

En 50470

Class B

62053 21

Measurement

Max Min Data

Demand

+

Led Impulse

Kwh

+

Kvarh

+