

ЭЛЕКТРОННАЯ ПРОДУКЦИЯ > ПРОДУКТЫ УПРАВЛЕНИЯ ЭНЕРГИЕЙ > СЧЁТЧИКИ
ЭЛЕКТРОЭНЕРГИИ

5100-1Q-V1

Артикул (SKU): 606810

3Ø счетчик энергии

Коммерческая информация

Код продажи продукта	606810
Единица Упаковки	1 шт.
Номер таможенного тарифа	903032009011
Вес за единицу, включая упаковку	0.34 kg.

Техническая информация

General

Connection Type	3P4W
Real Time Clock	
Current Connection Type	Direkt Baglantili (100A ya kadar)
Alarm	+

Energy Measurement

Number Of Tariffs	1
Number Of Sub Tariffs	
Number Of Reactive Measurement Zones	4
Energy Measurement Type	Import & Export kWh-kVArh
Partial Counter	
Balance Energy	

Current Measurement Input

Measuring Range	3x 0,15 .. 100A
-----------------	------------------------

Voltage Measurement Input

Measuring Range L N	100-300V AC
---------------------	--------------------

Measuring Range L L	173-520
---------------------	----------------

Power Quality Measurements

Harmonic Measurement Current And Voltage	31
--	-----------

Thdi	+
------	----------

Thdv	+
------	----------

Power Supply

Voltage	100-300V AC
---------	--------------------

Frequency	45-65Hz
-----------	----------------

Consumption	<3VA AC
-------------	-------------------

Mechanical Properties

Weight G	340
----------	------------

Protection Class	IP20
------------------	-------------

Mounting Type	Rail Mount
---------------	-------------------

Environmental Conditions

Operating Temperature	-25°C +50°C
-----------------------	--------------------

Storage Temperature	-25°C +70°C
---------------------	--------------------

Relative Humidity Non Condensing	Max. 80% (no condensation)
----------------------------------	-----------------------------------

Communication

Protocol	Modbus RTU
----------	-------------------

Baud Rate	1200-57600
-----------	-------------------

Parity	Odd, Even, None
--------	------------------------

Stop Bit	1
----------	----------

Slave Id	1-247
----------	--------------

Isolation	2750V RMS
-----------	------------------

Digital Output

Frequency	
-----------	--

Number Of Inputs	
Switched Voltage Range	
Isolation	

Digital Input

Number Of Inputs	
Input Type	
Isolation	

Other Measurements

Operating Time Counter	+
Open Time Counter	+
Power Failure Counter	+

Basic Electrical Measurements

Current	+
Voltage	+
Frequency	+
Active Power	+
Reactive Power	+
Apparent Power	+

Cable Cross Sections Power Supply Voltage Relay

multi-core	
Single Core	

Cable Cross Sections Current

multi-core	
Single Core	

Cable Cross Sections Digital Inputoutput Rs485 Analog Output

multi-core	
Single Core	

Measurement Class

En 50470	
62053 21	Class 0,5

Measurement

Max Min Data	+
Demand	+

Led Impulse

Kwh	
Kvarh	